# HP LaserJet Tank MFP 1602w Printer



Business capabilities with up to 5,000 pages of pre-filled toner and an ultra-low cost per page<sup>1</sup>

Discover business-ready capabilities and savings with HP LaserJet Tank MFP 1602w All-in-One Printer pre-filled with up to 5,000 pages of Original HP Toner<sup>1</sup>



Print Speed: Letter: Up to 23 ppm; First Page Out: As fast as 8 sec black

Print Resolution: Black (best): Up to 600 x 600 dpi Scan Resolution: Hardware: 600 x 1200 dpi; Optical: Up to 600 dpi Standard Connectivity: Hi-Speed USB (compatible with USB 2.0 specifications); 802.11a/b/g/n (2.4/5 GHz) Wi-Fi radio + BLE Mobile Printing Capability: HP Smart App; Apple AirPrint™; Mopria™ Certified; Wi-Fi® Direct Printing

Duty cycle: Monthly (letter): Up to 25,000 pages Display: Icon LCD

Paper Handling: 150 sheet input tray; 100 sheet output













### Get high-quality printing with ultra-low cost per page

- Engineered for high-volume printing pre-filled with 5,000 pages of toner in
- Help to save on refills with ultra high yield HP Toner Reload Kit.  $^{\!3}$
- Deliver exceptional quality with sharp text and bold blacks, page after page.

#### Easy toner refill in 15 sec with Original HP Toner.

- Easily refill Original HP Toner in 15 seconds.<sup>5</sup>
- Less downtime with 2,500 and 5,000-page HP Toner refill options. The Original HP Toner Reload Kit has an unique design, made with over 75% less plastic.

#### Full features for versatile productivity.

- Maximize your uptime with print speeds up to 22ppm.
- Easily handle tasks and get a lot from one device print, scan, copy.
- Print, scan, and share anytime, anywhere with HP Smart app. 8
- Low maintenance with long-life up to 50,000 page imaging drum.<sup>8</sup>

## HP LaserJet Tank MFP 1602w Printer Technical specifications

Functions	Print, copy, scan
Print speed black	A4: Up to 22 ppm; First page out: As fast as 8.0 sec
Print resolution	Black (best): Up to $600 \times 600$ dpi; Black (fine lines): Up to $600 \times 600$ dpi
Print technology	Laser
Print resolution technologies	600 x 400 dpi; 600 x 600 dpi
Print cartridges number	1 (black)
Standard print languages	PCLmS; URF; PWG
Printer smart software features	HP Auto-On/Auto-Off, HP Smart App
Scan type / Technology	Flatbed Contact Image Sensor (CIS)
Scan resolution	Hardware: 600 x 1200 dpi; Optical: Up to 600 dpi
Scan file format	JPEG, RAW(BMP), PNG, TIFF, PDF
Scan input modes	HP Smart App; and user applications via Twain
Scan size maximum	Flatbed: 216 x 297 mm
Bit depth / Grayscale levels	24-bit/256
Copy speed black	Copy speed: Up to 22 cpm
Standard connectivity	Hi-Speed USB (compatible with USB 2.0 specifications); 802.11a/b/g/n (2.4/5 GHz) Wi-Fi radio + BLE
Network capabilities	built-in WiFi 802.11b/g/n (2.4/5GHz)
Wireless capability	built-in WiFi 802.11b/g/n (2.4/5GHz)
Mobile printing capability <sup>4</sup>	HP Smart App; Apple AirPrint™; Mopria™ Certified; Wi-Fi® Direct Printing
Memory	Standard: 64 MB; Maximum: 64 MB SDRAM
Processor speed	500 MHz
Duty cycle	Monthly A4: Up to 25,000 pages
Recommended monthly page volume	250-2500
Media types supported	Plain paper, Heavy paper, Bond paper, Label, Light paper, Envelope
Media weight supported	60 to 163 g/m²
Media sizes supported	A6; A5; A4; No.10 Env; C5 Env; DL Env; B5 Env; B5(JIS); B6 (JIS); 216mm x 340mm; Custom
Media Sizes Custom	102 x 152 to 215.9 x 355.6 mm
Paper handling	Input Capacities: Up to 150 sheets Standard; Up to 10 envelopes Output Capacities: Up to 100 sheets Standard; No transparency support Duplex Options: Manual (driver support provided) Envelope feeder: No specific envelope feeder. Envelope can be supported in Tray 1 Standard paper trays: 1

What's in the box	2R3EBA HP Black Original LaserJet Tank Imaging Drum (~5000 page yield black toner provided), Power Cord, Setup Guide, Reference Guide, Regulatory/Support Flyers.
Replacement cartridges <sup>3</sup>	HP 154A Black Laser Jet Tank Toner Reload Kit (Yield ~2500 pages); HP 154X Black Laser Jet Tank Toner Reload Kit (Yield ~5000 pages);
Product dimensions	<b>W</b> x d x h: 368 X 326 X 255 mm (14.5 X 12.83 X 10 in); <b>Maximum:</b> 368 X 390.5 X 255 mm (14.5 X 15.4 X 10 in)
Product weight	7.9 kg (17.4 lb)
Warranty features	One-year limited hardware warranty. For more info, please visit us at https://support.hp.com
Energy star certified	No
Blue Angel Compliance	Yes, Blue Angel DE-UZ 219—only ensured when using Original HP supplies
Control panel	lcon LCD; 3 lights (Media, Wifi, Lid open); 10 buttons (WiFi, Down, Menu, Up, Copy, ID copy, Info, Resume, Cancel, Power)
Display description	lcon LCD
Software included	No CD inbox (except Indonesia and China Gov) Downloadable Software from hp.com or 123.hp.com #CD include HP Software Installer, Uninstaller, printer driver and other essential tools
Compatible operating systems	Windows 11; Windows 10; Windows 7; macOS 10.15 Catalina; macOS 11 Big Sur; macOS 12 Monterey; Linux
Compatible network operating systems	Windows Server 2008 R2 64-bit, Windows Server 2008 R2 64-bit (SP1), Windows Server 2012 64-bit, Windows Server 2012 R2 64-bit, Windows Server 2016 64-bit; Linux (For more information see http://developers.hp.com/hp-linux-imaging-and-printing)
Minimum system requirements	PC: Microsoft <sup>®</sup> Windowc <sup>®</sup> 11, 10, 7 SP1: 32-bit or 64-bit, 2 GB available hard disk space, Internet connection, Microsoft <sup>®</sup> Internet Explorer or Edge.; Mac: Apple <sup>®</sup> macOS v10.15 (catalina, macOS v11 Big Sur, macOS v12 Monterey, 2 GB HD; Internet required
Power	Power supply type: Internal (Built-in) power supply; Power requirements: Printer-110V-RNN: L1Z543A; Rated Voltage: 110-127V; Rated Current: 5.2A; Frequency: 50/60Hz, Printer-220V-RNM: L1Z543E; Rated Voltage: 220-240V; Rated Current: 2.9A; Frequency: 50/60Hz; Power consumption: Active printing: 390w, Ready: 2.7w, Sleep: 0.51w, Manual Off: 0.05w, Auto Off/Manual On: 0.05w, Auto-Off/Wake on LAN: 0.5w
Acoustics	Acoustic power emissions: 6.3 B(A)
Operating environment	Operating temperature range: 15 to 32.5°C; Recommended operating temperature: 17.5 to 25°C; Storage temperature range: -20 to 60°C; Non-operating humidity range: ; Operating humidity range: 10 to 80 %RH; Recommended humidity operating range: 30 to 70% RH
HP Service and Support options	U04TCE - HP 1y OnsiteExchange LJ Tank MFP Mid SVC; U04TDE - HP 2y OnsiteExchange LJ Tank MFP Mid SVC; U04TEE - HP 3y OnsiteExchange LJ Tank MFP Mid SVC; U04TGE - HP 4y OnsiteExchange LJ Tank MFP Mid SVC; U04TEE - HP 5y OnsiteExchange LJ Tank MFP Mid SVC; U04TWE - HP 3y NBD AdV Exch LJ Tank MFP Mid SVC; U04TWE - HP 3y NBD AdV Exch LJ Tank MFP Mid SVC; U04TWE - HP 3y NBD AdV Exch LJ Tank MFP Mid SVC; U04TWE - HP 3y AdV Exchange LJ Tank MFP Mid SVC; U04TWE - HP 3y AdV Exchange LJ Tank MFP Mid SVC; U04TWE - HP 3Y ADVE EXCHANGE LJ TANK MFP MID SVC; U04TWE - HP 4y AV Exchange LJ Tank MFP MID SVC; U04TWE - HP 4y RTD LJ Tank MFP MID SVC; U04TWE - HP 4y RTD LJ Tank MFP MID SVC; U04TWE - HP 4y RTD LJ TANK MFP MID SVC; U04TWE - HP 4y RTD LJ TANK MFP MID SVC; U04TWE - HP 4y RTD LJ TANK MFP MID SVC; U04TWE - HP 4y RTD LJ TANK MFP MID SVC; U04TWE - HP 4y RTD LJ TANK MFP MID SVC; U04TWE - HP 4y RTD LJ TANK MFP MID SVC; U04TWE - HP 4y RTD LJ TANK MFP MID SVC; U04TWE - HP 4y RTD LJ TANK MFP MID SVC; U04TWE - HP 4y RTD LJ TANK MFP MID SVC; U04TWE - HP 4y RTD LJ TANK MFP MID SVC; U04TWE - HP 4y RTD LJ TANK MFP MID SVC; U04TWE - HP 4y RTD LJ TANK MFP MID SVC; U04TWE - HP 4y RTD LJ TANK MFP MID SVC; U04TWE - HP 4y RTD LJ TANK MFP MID SVC; U04TWE - HP 4y RTD LJ TANK MFP MID SVC; U04TWE - HP 4y RTD LJ TANK MFP MID SVC; U04TWE - HP 4y RTD LJ TANK MFP MID SVC; U04TWE - HP 4y RTD LJ TANK MFP MID SVC; U04TWE - HP 4y RTD SVC TANK MTD SVC TANK MID SVC TANK MTD SVC T

Learn more at hp.com

1 HP Auto-On/Auto-Off Technology capabilities subject to printer and settings; may require a firmware upgrade. <sup>2</sup>Requires the HP Smart app download. For details on local printing requirements see www.hp.com/go/mobileprinting. Certain features/software are available in English language only and differ between desktop and mobile applications. Subscription may be required; subscription may not be available in all countries. See details: HPSmart.com at Internet access required and must be purchased separately. HP account required for full functionality. List of supported operating systems available in app stores. <sup>4</sup> HP Black Original Laser let? Tank Imaging During Internout.ord. <sup>4</sup> To Super let a place bett better with a formation included with your printers ese ethtp://www.hp.com/go/noneyield. <sup>4</sup> WH-FI Direct. <sup>4</sup> Toornote: Mobile device needs to be connected to WH-FI Direct. <sup>4</sup> Signal of a WH-FI Direct. <sup>4</sup> Signal of a

